

## Calculating Output Amplitude Accuracy using dB

October 01, 2018

Some specifications, like the SDG800 and 1000 series, describe the vertical accuracy using dB

The SDG1000, for example, states:

Vertical Accuracy =  $\pm (0.3 \text{ dB} + 1 \text{ mV})$

First, let's convert the dB part...

$$\text{Vertical Accuracy(dB)} = 20 \log (1 + (\text{Error}(\%)/100))$$

$$\pm 0.3 \text{ dB} = 20 \log (1 + (\text{Error}(\%)/100))$$

$$\text{Error} (\%) = 3.5\%$$

So, if we set the voltage output to 1 V:

$$\text{Vertical Accuracy} = \pm (0.3 \text{ dB} + 1 \text{ mV}) = \pm ((1 \text{ V}) * 3.5\% + 1 \text{ mV}) = \pm 0.036$$

So, for a 1 V set point, an in-tolerance sourced value would lie in the span of 1 +/- 0.036 V



### **North American Headquarters**

SIGLENT Technologies NA  
6557 Cochran Rd Solon, Ohio 44139  
Tel: 440-398-5800  
Toll Free: 877-515-5551  
Fax: 440-399-1211  
[info@siglent.com](mailto:info@siglent.com)  
[www.siglentamerica.com/](http://www.siglentamerica.com/)

### **European Sales Offices**

SIGLENT TECHNOLOGIES GERMANY GmbH  
Staetzlinger Str. 70  
86165 Augsburg, Germany  
Tel: +49(0)-821-666 0 111 0  
Fax: +49(0)-821-666 0 111 22  
[info-eu@siglent.com](mailto:info-eu@siglent.com)  
[www.siglenteu.com](http://www.siglenteu.com)

### **Asian Headquarters**

SIGLENT TECHNOLOGIES CO., LTD.  
Blog No.4 & No.5, Antongda Industrial Zone,  
3rd Liuxian Road, Bao'an District,  
Shenzhen, 518101, China.  
Tel: + 86 755 3661 5186  
Fax: + 86 755 3359 1582  
[sales@siglent.com](mailto:sales@siglent.com)  
[www.siglent.com/ens](http://www.siglent.com/ens)