

# Programming Example: Controlling an SPD power supply via Sockets over LAN

January 04, 2021

Here is a Python 3.6 example of using sockets to control an SPD power supply connected to a computer using LAN.

Here is a zip file of the working program: [PythonSocket\\_SPD\\_10232019.zip](#)

NOTE: The SPD uses VXI-11 protocol for LAN. On some systems, it is helpful to use the VXI-11 format for the IP address:

“TCPIP::ip.add.re.ss::INSTR”

Here is the program in full:

```
#!/usr/bin/env python
#-*- coding:utf-8 -*-
#-----
# The short script is a example that open a socket, sends a query,
# print the return message and closes the socket.
#
#No warranties expressed or implied
#
#SIGLENT/JAC 05.2018
#
#-----
import socket # for sockets
import sys # for exit
import time # for sleep
#-----

remote_ip = "192.168.55.109" # should match the instrument's IP address
port = 5025 # the port number of the instrument service

#Port 5024 is valid for the following:
#SIGLENT SDS1202X-E, SDG1/2X Series, SDG6X Series
#SDM3055, SDM3045X, and SDM3065X
#
#Port 5025 is valid for the following:
#SIGLENT SVA1000X series, SSA3000X Series, and SPD3303X/XE

count = 0
def SocketConnect():
    try:
        #create an AF_INET, STREAM socket (TCP)
```

```
s = socket.socket(socket.AF_INET, socket.SOCK_STREAM)
except socket.error:
    print ('Failed to create socket.')
    sys.exit();
try:
    #Connect to remote server
    s.connect((remote_ip , port))
except socket.error:
    print ('failed to connect to ip ' + remote_ip)
return s
def SocketClose(Sock):
    #close the socket
    Sock.close()
    time.sleep(1)

def main():
    global remote_ip
    global port
    global count

    # Body: send the SCPI commands *IDN? 10 times and print the return message
    s = SocketConnect()
    for i in range(1):
        s.sendall(b'OUTPUT CH1,ON')
        #s.sendall(b'\n')
        time.sleep(5)
        s.sendall(b'OUTPUT CH1,OFF')
        #s.sendall(b'\n')
        time.sleep(5)
        print (str(count))
        count = count + 1
    SocketClose(s)
    print('Test complete. Exiting program')
    sys.exit

if __name__ == '__main__':
    proc = main()
```



### **North American Headquarters**

SIGLENT Technologies NA  
6557 Cochran Rd Solon, Ohio 44139  
Tel: 440-398-5800  
Toll Free: 877-515-5551  
Fax: 440-399-1211  
[info@siglent.com](mailto:info@siglent.com)  
[www.siglentamerica.com/](http://www.siglentamerica.com/)

### **European Sales Offices**

SIGLENT TECHNOLOGIES GERMANY GmbH  
Staetzlinger Str. 70  
86165 Augsburg, Germany  
Tel: +49(0)-821-666 0 111 0  
Fax: +49(0)-821-666 0 111 22  
[info-eu@siglent.com](mailto:info-eu@siglent.com)  
[www.siglenteu.com](http://www.siglenteu.com)

### **Asian Headquarters**

SIGLENT TECHNOLOGIES CO., LTD.  
Blog No.4 & No.5, Antongda Industrial Zone,  
3rd Liuxian Road, Bao'an District,  
Shenzhen, 518101, China.  
Tel: + 86 755 3661 5186  
Fax: + 86 755 3359 1582  
[sales@siglent.com](mailto:sales@siglent.com)  
[www.siglent.com/ens](http://www.siglent.com/ens)