

# Programming Example: SDS Oscilloscope screen image capture using Python over LAN

March 08, 2019

Here is a brief code example written in Python 3.4 that uses a socket to pull a display image (screenshot) from a SIGLENT SDS1000X-E scope via LAN and save it to the local drive of the controlling computer.

**NOTE:** This program saves the picture/display image file in the same directory that the .py file is being run from. It will overwrite any existing file that has the same name.

Download Python 3.4, connect a scope to the LAN using an Ethernet cable, get the scope IP address, and run the attached .PY program to save a bitmap (BMP) image of the oscilloscope display.

You can download the .PY file here: [Python\\_Socket\\_SDS\\_SCDP.zip](#)

## Tested with:

Python 3.4  
SDS1202X-E  
SDS1104/1204X-E  
SDS2000X-E Models  
SDS5000X Models

```
#!/usr/bin/env python 3.4.3
#-*- coding:utf-8 -*-
#-----
#The short script is a example that open a socket, sends a query to return a
#screen dump from the scope, saves the screen dump as a BMP in the python
folder,
#and closes the socket.
#
#Currently tested on SDS1000X-E,2000X-E, and 5000X models
#
#No warranties expressed or implied
#
#SIGLENT/JAC 03.2019
#
#-----
import socket # for sockets
import sys # for exit
import time # for sleep
#-----
```

```
remote_ip = "192.168.55.100" # should match the instrument's IP address
port = 5025 # the port number of the instrument service
```

```
def SocketConnect():
    try:
        #create an AF_INET, STREAM socket (TCP)
        s = socket.socket(socket.AF_INET, socket.SOCK_STREAM)
    except socket.error:
        print ('Failed to create socket.')
        sys.exit();
    try:
        #Connect to remote server
        s.connect((remote_ip , port))
        s.setblocking(0) # non-blocking mode, an exception occurs when no data
is detected by the receiver
        #s.settimeout(3)
    except socket.error:
        print ('failed to connect to ip ' + remote_ip)
    return s
```

```
def SocketQuery(Sock, cmd):
    try :
        #Send cmd string
        Sock.sendall(cmd)
        Sock.sendall(b'\n') #Command termination
        time.sleep(1)
    except socket.error:
        #Send failed
        print ('Send failed')
        sys.exit()
```

```
data_body = bytes()
while True:
    try:
        time.sleep(0.01)
        server_replay = Sock.recv(8000)
        #print(len(server_replay))
        data_body += server_replay
    except BlockingIOError:
        print("data received complete..")
        break
```

```
return data_body
'''
```

```
PACK_LEN = 768067#the packet length you will receive;
#SDS5000X is 2457659;SDS1000X-E/2000X-E is 768067
had_received = 0
data_body = bytes()
while had_received &lt; PACK_LEN:
```

```
        part_body= Sock.recv(PACK_LEN - had_received)
        data_body += part_body
        part_body_length = len(part_body)
        #print('part_body_length', part_body_length)
        had_received += part_body_length
    return data_body
'''

def SocketClose(Sock):
    #close the socket
    Sock.close()
    time.sleep(5)

def main():
    global remote_ip
    global port
    global count

    #Open a file
    file_name = "SCDP.bmp"

    # Body: Open a socket, query the screen dump, save and close
    s = SocketConnect()
    qStr = SocketQuery(s, b'SCDP') #Request screen image
    print(len(qStr))
    f=open(file_name,'wb')
    f.write(qStr)
    f.flush()
    f.close()

    SocketClose(s)
    sys.exit

if __name__ == '__main__':
    proc = main()
```



### **North American Headquarters**

SIGLENT Technologies NA  
6557 Cochran Rd Solon, Ohio 44139  
Tel: 440-398-5800  
Toll Free: 877-515-5551  
Fax: 440-399-1211  
[info@siglent.com](mailto:info@siglent.com)  
[www.siglentamerica.com/](http://www.siglentamerica.com/)

### **European Sales Offices**

SIGLENT TECHNOLOGIES GERMANY GmbH  
Staetzlinger Str. 70  
86165 Augsburg, Germany  
Tel: +49(0)-821-666 0 111 0  
Fax: +49(0)-821-666 0 111 22  
[info-eu@siglent.com](mailto:info-eu@siglent.com)  
[www.siglenteu.com](http://www.siglenteu.com)

### **Asian Headquarters**

SIGLENT TECHNOLOGIES CO., LTD.  
Blog No.4 & No.5, Antongda Industrial Zone,  
3rd Liuxian Road, Bao'an District,  
Shenzhen, 518101, China.  
Tel: + 86 755 3661 5186  
Fax: + 86 755 3359 1582  
[sales@siglent.com](mailto:sales@siglent.com)  
[www.siglent.com/ens](http://www.siglent.com/ens)