

## SDS2000X Firmware Update Instructions

**Note: during the updating, do not cut off the power or pull out the U-disk.**

1. Please firstly unzip the firmware file (.ads) in the update package to a U-disk.
2. Insert the U-disk.
3. Press **Utility** and then **Next Page** to get to the third page of the UTILITY function menu.




Figure 1 UTILITY function menu

4. Press **Update** and then choose **Firmware** to enter the file system.




Figure 2 File system

- Use the universal knob to select the right update firmware which should be with an ADS postfix, and then press the **Press To Update** softkey, then the **Single** button to perform upgrade program. It will take about 5~6 minutes.



Figure 3 Press the Single button to start the upgrade according to the prompt



Figure 4 There will be a progress bar prompt during the upgrade process.

- Restart the oscilloscope when comes out the prompting “Update success! Please Restart The SPO!”




Figure 5 Update successfully

**Note: during the updating, do not cut off the power or pull out the U-disk.**