



## SDG5000 Firmware Update Instructions

**WARNING: DO NOT shut off the instrument until the update is completed.**


1. Copy the update file (\*.ads) to a FLASH type U-disk, and then connect the U-disk to the USB host port of the instrument.



2. Press the “Utility” key on the front panel, and then softkey “More 1of 2 -> Update”, to enter the interface of the file browser.



3. Select “USB Device” thru the knob on the front panel, press “Browser” to switch “Directory” to “File”(as shown in the following photo), and then select the correct ADS file using the knob.



4. Press "Recall" to start the update. A progress bar is displayed during the update. After the progress bar shows the message "The upgrade procedure is completed. Please restart your generator.", please restart the generator manually.

**WARNING: DO NOT shut off the instrument until the update is completed.**